

BOBOVR

BATTERY PACK COMPATIBLE WITH QUEST2
B2 battery pack needs to be used
with M2pro strap



www.bobovr.com

Product parameters

Function	Head size adjustment range	460-620mm(18.2-24.4inch)	
	Charging method	Magnetic removable battery pack	
	Input/Output	DC5V 2.6A MAX	
Battery pack parameters	Battery pack	Battery Type	Li Battery
		Battery energy	3.7V/5200mAh,19.24Wh
		Rated Capacity	5V/1.5A,3200mA
		0%-100% charging time	About 3 hours
		0%-80% charging time	About 2 hours
	Auto shutdown	When there is no external charging, it will automatically shut down within 40 seconds;	
	Safety protection	Support overcharge protection, overdischarge protection, overcurrent protection	
		Support short circuit protection, support high and low temperature protection	
	Operating temperature	0℃-40℃	



from XIAOZHAI

单页尺寸: 43MM X 79MM

Product introduction

BOBOVR B2 is a new battery pack accessory launched by bobovr. It can be flexibly matched with bobovr series products as a replaceable energy supplement. It has the characteristics of small volume and convenient installation

Product diagram



1. Power input / output USB-C interface
2. work indicator
3. Button
4. Power indicator
5. Magnet power interface

usage method

Adsorb B2 to the magnetic suction interface of M2 pro. When the connection is successful, it will prompt a Ding, the ring lamp and electricity lamp will light up and start to supply power to quest2.

Note: when the plug cable of M2 Pro is not plugged in or quest2 is fully charged, the battery will turn off within 40 seconds.



Before

Product introduction



After

You can use the original quest2 charger or other commonly used usb-c charger to charge the B2 battery pack. After the B2 battery pack is fully charged, the quest2 can be fully charged or the battery life can be increased by about 3 hours.

Power display: B2 battery pack has four power indicators, indicating 0%-25%, 25%-50%, 50%-75% and 75% -100% power respectively.

Tips

- *Please use a charger with safety certification and support DC 5V2A or 5V3A. It is strictly prohibited to charge with a charger that does not support DC 5V;
- *It is forbidden to throw the product into the fire or water, and it is forbidden to expose to the sun or drench with water;
- *It is forbidden to disassemble, strike or drop the product without authorization;
- *When not in use for a long time, please charge the battery to more than 60%, store it indoors in a normal temperature and dry environment, and charge the mobile power supply every 5 months;
- *Please do not wash or clean the product with chemicals;
- *In case of liquid leakage, peculiar smell or smoke, please stop using it immediately.